

## Elecraft DL1 Dummyload/Wattmeter

$$P=((V \times 1.414) + 0.15)^2 / 50$$

<b>volts</b>	<b>watts</b>	<b>volts</b>	<b>watts</b>
3.00	0.39	8.00	2.63
3.25	0.45	8.25	2.79
3.50	0.52	8.50	2.96
3.75	0.59	8.75	3.14
4.00	0.67	9.00	3.32
4.25	0.76	9.25	3.50
4.50	0.85	9.50	3.69
4.75	0.94	9.75	3.88
5.00	1.04	10.00	4.08
5.25	1.15	10.25	4.29
5.50	1.26	10.50	4.50
5.75	1.37	10.75	4.71
6.00	1.49	11.00	4.93
6.25	1.62	11.25	5.16
6.50	1.75	11.50	5.39
6.75	1.88	11.75	5.62
7.00	2.02	12.00	5.86
7.25	2.16	12.25	6.11
7.50	2.31	12.50	6.35
7.75	2.47	12.75	6.61